



www.allenlighting.com.au
ABN 99 099 066 083

Z series

Features:

- Opal acrylic diffuser.
- Available with 32w T8 circular lamps and ferro-magnetic control gear.
- Available with 22w and 40w T8 ferro-magnetic or electronic control gear.
- Available with T5 energy efficient fluorescent lamps and electronic control gear.
- Dimming options available in T5.(D)
- Complies with EMC framework
- Complies with Australian electrical standards.

Applications:

- Ceiling or wall mount.
- Suitable for commercial and residential use.
- Kitchens, living areas and home offices.

Code	Ballast	Lamp and base
Z218E	Electronic A2	2x18w TCL 2G11
Z224E	Electronic A2	2x24w TCL 2G11
Z22	Ferro-magnetic B2	1x22w T8 circular G10q
Z22H	Ferro-magnetic B2	1x22w T8 circular G10q
Z22T	Ferro-magnetic B2	1x22w T8 circular G10q
Z22TH	Ferro-magnetic B2	1x22w T8 circular G10q
ZT522Q	Electronic A2 R	1x22w T5 circular G10q
ZT522X	Electronic A2	1x22w T5 circular 2GX13
ZT522XD	Electronic A1	1x22w T5 circular 2GX13
Z32	Ferro-magnetic B2	1x32w T8 circular G10q
Z32H	Ferro-magnetic B2	1x32w T8 circular G10q
Z32T	Ferro-magnetic B2	1x32w T8 circular G10q
Z32TH	Ferro-magnetic B2	1x32w T8 circular G10q
ZT532Q	Electronic A2 R	1x32w T5 circular G10q
Z40	Electronic A2	1x40w T8 circular G10q
Z40E	Electronic A2	1x40w T8 circular G10q
Z40ET	Electronic A2	1x40w T8 circular G10q
Z40H	Ferro-magnetic B2	1x40w T8 circular G10q
Z40T	Ferro-magnetic B2	1x40w T8 circular G10q
Z40TH	Ferro-magnetic B2	1x40w T8 circular G10q
ZT540Q	Electronic A2 R	1x40w T5 circular G10q
ZT540X	Electronic A2	1x40w T5 circular 2GX13
ZT540XD	Electronic A1	1x40w T5 circular 2GX13
ZT555X	Electronic A2	1x40w T5 circular 2GX13
ZT555XD	Electronic A1	1x40w T5 circular 2GX13
ZT562X	Electronic A2	1x22+40w T5 circular 2GX13
Z72E	Electronic A2	1x32+40w T8 circular G10q
Z72ET	Electronic A2	1x32+40w T8 circular G10q

